

C1200+ DVB-C Meter





Key Benefits

- Analog TV Analysis: Level, Tilt, C/N, Scan and Trunk Voltage
- Digital TV Analysis: Power Level, MER and BER
- 128×64 pixels LCD with back-light
- Large lithium battery capacity, over 4 hours working time
- Software upgrade and channel plan edit via USB interface

C1200+ DVB-C Meter is specially designed for installation and field technicians seeking to quickly ensure the quality of digital and analog cable services. With streamlined appearance design and simple user interface, C1200+ offers the most cost effective choice for a variety of applications.

Specifications

Analog CATV	
Frequency Range	5~1010MHz
Level	30~120dBuV
Accuracy	±2.0dB
RBW	300K
C/N	>50dB
C/N Accuracy	±3.0dB
Others	Channel Scan,Tilt,Trunk Voltage
DVB-C	
Frequency Range	46~1010MHz
Power Level	40dBuV ~ 110dBuV
Power Level Accuracy	±2.0dB
MER	>40
MER Accuracy	±2.0dB
BER	1E-3~1E-9
Modulation Type	16/32/64/128/256QAM(J.83A/C), 64/256QAM(J.83B)
SR	4~7Msps
Interface	
RF Input	75Ω J Type
AC Adapter	12V/1.2A
USB	Mini-USB
Battery	
Capacity	7.4V/1.6AH
Working Time	>4 hours
Charging Time	3 hours
Other Specifications	
Dimensions (H×W×D)	153mm x 93mm x 42mm (6.0" x 3.7" x 1.7")
Weight	358g



Ordering Information

SKU No.	Description
C1200+	Mini Signal Level Meter, 46 MHz ~ 1010 MHz, 75Ω or BNC
DS2400-703	2-Prong Power Cord plus Ground (Europe except UK)
308-0022-01	3-Prong Power Cord plus Ground (US)
DS2400-705	3-Prong Power Cord plus Ground (UK)
DS2400-704	3-Prong Power Cord plus Ground (Australia)
C1200-004	English Instruction Manual (hard copy)
SFL10-KK	Toko Type F(f) to F(f) Connector